

Accessories

Flexible shaft

photo: 1910C4-5

Adapter set (40Vmax)



Part No. 1910J4-4 For PDC01 and PDC1200

Battery case H set

Battery case L set Part No. 1910J1-0 For BL4050F, BL4080F



Charging Time

40 Thereon	DC40RA	DC40RC
BL4020 2.0Ah	22 min	30 min
BL4025 2.5Ah	28 min	38 min
*1 BL4040 4.0Ah	45 min	67 min
*1*2 BL4050F 5.0Ah	50 min	85 min
*1*2 BL4080F 8.0Ah	76 min	170 min

*1 Recommended battery *2 Use with Battery case L set

Portable Power Pack (use with Adapter set and Battery case H set) PDC01

Powered by up to four 18V LXT batteries





PDC1200

Powered by 36V-40Vmax built-in battery





Cordless Concrete Vibrator VR001G / VR003G / VR004G

_		
Electronic 2-Speed	Max output	w/ PDC1200: 550W
	Diameter of vibrator	VR001G: -, VR003G: 32 mm (1-1/4"), VR004G: 38 mm (1-1/2")
Constant Speed	Flexible Shaft Assembly Length	VR001G: -, VR003G: 1.2, 1.7, 2.4 m (3.9, 5.6, 7.9 ft), VR004G: 1.2, 2.4 m (3.9, 7.9 ft)
	Vibrations Per Minute (VPM)	Power mode: 15,500, Normal mode: 12,000
	Work amount on a full battery charge	w/ 32mm-1.2m shaft, w/ BL4040, Power mode: 35 min
		w/ 32mm-1.2m shaft, w/ BL4040, Normal mode: 50 min
	Sound Pressure Level	80 dB(A)
	Vibration Level	w/ Flexible shaft: 4.9 m/s²
	Dimensions (L x W x H)	VR001G: w/o Flexible shaft, w/ BL4020/BL4025/BL4040: 282 x 112 x 258 mm (11-1/8 x 4-3/8 x 10-1/8")
		w/o Flexible shaft, w/ BL4050F/BL4080F: 296 x 112 x 299 mm (1-5/8 x 4-3/8 x 11-3/4")
		VR003G: w/ 32mm-1.2m shaft, w/ BL4020/BL4025/BL4040: 1,495 x 112 x 258 mm (59 x 4-3/8 x 10-1/8")
		w/ 32mm-2.4m shaft, w/ BL4050F/BL4080F: 2,509 x 112 x 299 mm (99 x 4-3/8 x 11-3/4")
		VR004G: w/ 38mm-1.2m shaft, w/ BL4020/BL4025/BL4040: 1,493 x 112 x 258 mm (58-3/4 x 4-3/8 x 10-1/8")
		w/ 38mm-2.4m shaft, w/ BL4050F/BL4080F: 2,507 x 112 x 299mm (98-1/2 x 4-3/8 x 11-3/4")
	Net weight	VR001G: 2.1 - 3.4 kg (4.6 - 7.5 lbs.), VR003G: 4.2 - 7.4 kg (9.4 - 16.4 lbs.), VR004G: 5.2 - 7.8 kg (11.5 - 17.3 lbs.)

The weight may differ depending on the attachment(s), including the battery cartridge. The lightest and heaviest combination, according to EPTA-Procedure 01/2014, are shown in the table.

Standard Equipment: VR001G: Wrench, VR003G, VR004G: Wrench, Battery, Charger

Items of standard equipment and specifications may vary by country or area.

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN 202205



Cordless Concrete Vibrator VR001G / VR003G / VR004G







VR001G Tool only without Flexible shaft




VR003G

with Flexible shaft ø32



VR004G



638-1.2m or 038-2.4m





Constant speed control allows for stable compaction work.

Vibration speed

Low



High efficiency Brushless DC motor

Suitable for a wide range of jobsites



Power mode

For a wide range of concrete compaction, such as of soil floors, pillars, and mat foundations.

Vibration per minute

15,500 min-1

Work amount (on a full battery charge)

35 min

High

(With ø32mm-1.2m shaft and BL4040 battery)

Ideal for delicate works, such as step finishing or closure of not to flow out of the mold. **Vibration per minute** 12,000 min⁻¹ Work amount (on a full battery charge) **50** min

Normal mode

temporary construction openings, where concrete is required

(With ø32mm-1.2m shaft and BL4040 battery)

Compatible with large diameter shafts

VR001G

Predecessor model


Workload

larger vibration part diameter than the current model and transmits vibration to a wider range to improve compaction efficiency

Model	Vibrator diameter	Flexible shaft length
VR001G	-	-
VR003G	ø32mm	1.2, 1.7, 2.4m
VR004G	ø38mm	1.2, 2.4m

Switch cover

protects switch trigger and lock-on button from being blocked by adhered and hardened material such as concrete.



Various Battery covers

are available for all recommended or compatible batteries



The supplied Battery cover is compatible with BL4020/ BL4025/BL4040.

The following Battery covers are also available as an option:

- · Battery case L set for BL4050F/BL4080F
- · Battery case H set for PDC01/PDC1200



eXtreme Protection Technology

