

Comfort/Lifestyle

Cordless Job Site Speaker



Cordless Cooler & Warmer Box



Cordless Kettle



Cordless Coffee Maker



Continuous run time (approx): hour
On a single full battery charge

Model No.	MR009G					DMR056						DMR055					
	40Vmax					18V											
Battery	PDC1200	BL4020	BL4025	BL4040	BL4050F	BL1815N	BL1820B	BL1830B	BL1840B	BL1850B	BL1860B	BL1815N	BL1820B	BL1830B	BL1840B	BL1850B	BL1860B
Radio	340	20	24	36	51	13	17	24	34	44	53	15	20	28	40	52	63
Flashlight (H/L)	440/813	26/49	31/58	46/86	66/122	9.0/17	12/23	16/32	23/45	30/58	37/70	-	-	-	-	-	-
Lantern (4 sides/3 sides)	227/313	13/18	16/22	24/33	34/47	4.5/6.5	6.0/8.5	8.5/12	12/17	16/22	19/26	4.5/6.5	6.0/8.5	8.5/12	12/17	16/22	19/26
Radio+Lantern (4 sides)	140	8.0	10	14	21	3.5	4.5	6.5	9.0	12	14	3.5	4.5	6.5	9.0	12	14

Charging Time

Model No.	Charger	40V max		18V LITHIUM-ION		18V LITHIUM-ION		18V LITHIUM-ION		
		Battery	Fast Charging	Battery	Fast Charging	Battery	Fast Charging	Battery	Fast Charging	
PDC1200	DC4001	BL4020 2.0Ah	22 min	30 min	BL1815N 1.5Ah	15 min	30 min	BL1840B 4.0Ah	36 min	90 min
		BL4025 2.5Ah	28 min	38 min	BL1820B 2.0Ah	24 min	45 min	BL1850B 5.0Ah	45 min	110 min
		BL4040 4.0Ah	45 min	67 min	BL1830B 3.0Ah	22 min	60 min	BL1860B 6.0Ah	55 min	130 min
		BL4050F 5.0Ah	50 min	85 min						

Cordless Radio with Lantern
MR009G / DMR056 / DMR055

	MR009G / DMR056	DMR055
Standard Equipment :	Frequency Band FM: 87.5-108 MHz / DAB: 174.928-239.200 MHz / DAB+: 174.928-239.200 MHz	FM: 87.5-108 MHz / AM: 522-1,710 kHz
Strap Hook	Speaker Size Ø57 mm	Ø57 mm
Battery and charger are sold separately	Illuminance	Lantern, Daylight white, 4 sides, High / Low: 145 / 72 or more lx
		Lantern, Neutral white, 4 sides, High / Low: 140 / 70 or more lx
		Lantern, Warm white, 4 sides, High / Low: 130 / 65 or more lx
Luminous flux		Flashlight, High / Low: 1,000 / 500 or more lx
		Lantern, Daylight white, 4 sides, High / Low: 310 / 155 or more lm
		Lantern, Neutral white, 4 sides, High / Low: 300 / 150 or more lm
Bluetooth		Lantern, Warm white, 4 sides, High / Low: 260 / 130 or more lm
		Flashlight, High / Low: 200 / 100 or more lm
		Version: 5.0
Dimensions (L x W x H)		Profile: A2DP, SCMS-T, AVRCP
		Supported Codec: SBC / AAC
		Max Transmission Range (Optimum): 10 m (33 ft)
Net weight		Transmission Power Class: 2
		Compatible Bluetooth Profile: A2DP
	w/o Battery: 126 x 127 x 240 mm (5 x 5 x 9-1/2")	w/o Battery: 126 x 127 x 240 mm (5 x 5 x 9-1/2")
	MR009G: 1.6 - 2.2 kg (3.5 - 4.9 lbs.) / DMR056: 1.3 - 1.6 kg (2.9 - 3.5 lbs.)	1.2 - 1.6 kg (2.7 - 3.5 lbs.)

Not covered by EPTA-Procedure
Items of standard equipment and specifications may vary by country or area.

Makita Corporation

3-11-8 Sumiyoshi-cho, Anjo, Aichi, 446-8502 Japan

PRINTED IN JAPAN 202205



photo: MR009G

photo: DMR056

Model	Light Options	Flashlight LEDs
MR009G	Lantern: 20 LEDs Light tone and color: Daylight white, Neutral white, Warm white	Flashlight: 1 LED
DMR056	Lantern: 20 LEDs Light tone and color: Daylight white, Neutral white, Warm white	Flashlight: 1 LED
DMR055	Lantern: 20 LEDs Light tone and color: Warm white	Flashlight: 1 LED

XGT
40V Li-ion
max

18V
LITHIUM-ION



photo: MR009G



photo: MR009G



photo: DMR056

Cordless Radio with Lantern that can be used at work, play, or anytime

Lantern with 3 light tone settings

MR009G / DMR056 only



Warm white

You will feel relaxed.
(about 2,500K)

Neutral white


(about 3,500K)

Daylight white

You can easily read what is written / printed.
(about 5,000K)

Switch

MR009G / DMR056



- Brightness setting button (2 stages) (MR009G / DMR056 only)
- Lantern light tone setting button (3 tones) (MR009G / DMR056 only)
- On/off and Mode select button

DMR055



USB output port

MR009G / DMR056 only

- With USB output switch
- With Auto-off function
- Type A, 1 port, DC5V/ 2.4A



Foldable hanging hook



Strap with hook allows to illuminate downwards, for example, from the ceiling to the floor

Flashlight

MR009G / DMR056 only



- Daylight white single LED
- Brightness settings (2 stages)

Lens guard also works as an FM antenna.

LCD digital display

Cordless Radio with Lantern

XGT 40V <small>Li-ion</small> max	18V LITHIUM-ION	18V LITHIUM-ION										
 <p>MR009G Bluetooth dab+ XPT</p> <table border="1"> <tr> <td>Lantern 20 LEDs</td> <td>Light tone and color Daylight white</td> </tr> <tr> <td>Flashlight 1 LEDs</td> <td>Neutral white Warm white</td> </tr> </table>	Lantern 20 LEDs	Light tone and color Daylight white	Flashlight 1 LEDs	Neutral white Warm white	 <p>DMR056 Bluetooth dab+ XPT</p> <table border="1"> <tr> <td>Lantern 20 LEDs</td> <td>Light tone and color Daylight white</td> </tr> <tr> <td>Flashlight 1 LEDs</td> <td>Neutral white Warm white</td> </tr> </table>	Lantern 20 LEDs	Light tone and color Daylight white	Flashlight 1 LEDs	Neutral white Warm white	 <p>DMR055 XPT</p> <table border="1"> <tr> <td>Lantern 20 LEDs</td> <td>Light tone and color Warm white</td> </tr> </table>	Lantern 20 LEDs	Light tone and color Warm white
Lantern 20 LEDs	Light tone and color Daylight white											
Flashlight 1 LEDs	Neutral white Warm white											
Lantern 20 LEDs	Light tone and color Daylight white											
Flashlight 1 LEDs	Neutral white Warm white											
Lantern 20 LEDs	Light tone and color Warm white											

Continuous run time (approx) On a single full battery charge

with BL4050F				with BL1850B				with BL1850B		
Radio	Radio+Lantern	Lantern	Flashlight	Radio	Radio+Lantern	Lantern	Flashlight	Radio	Radio+Lantern	Lantern
51h	21h	34h	66h	44h	12h	16h	30h	52h	12h	16h

Multi functions

MR009G / DMR056

Lantern	Flashlight	FM radio (9 stations)
dab+ (9 stations)	USB output port	Bluetooth

DMR055

Lantern	AM / FM radio (9 stations)
---------	----------------------------



XPT

photo: MR009G